PCCS9RW

LIGHT SWITCH CONTROL

The high current PCCS9RW provides complete control of nine auxiliary light functions and features built-in relays for lightbars that use standard switching. Designed for ease of use, the PCCS9RW includes LED backlighting for easy nighttime use and press-on labels for customization.

Back View

FEATURES

- · Complete control of nine auxiliary light functions
- · 20 amp relays
- Three-position slide switch
- · Six programmable push-button switches can be easily programmed for push-on, push-off, momentary, flashing, or timed output operations
- · Any switch can be programmed to activate any combination of the relay outputs or any push-button
- · Any switch can be programmed to enable siren functions
- · One auxiliary input for easy siren function duplication to other units
- · Easy to clone to multiple controllers
- · Individual 20 amp fused outputs
- •72 press-on legend tabs for customization
- · Legend buttons feature LED backlighting for nighttime viewing
- · Active switches are easily identified by a Red indicator light located below each legend button
- · Momentary switch type is available for use with low power, gun lock, and other momentary applications
- · Includes a universal bail bracket strap mounting kit for over or under dash mounting
- Designed to stack-mount with the WS295 Series siren amplifiers or Traffic Advisor control head

SPECS

Dimenstions: 6 1/8" (156mm) L x 1 7/8" (47mm) H x

6 1/4" (159mm) D

Weight: 1.75 lbs (0.8kg) Warranty: 2-Year warranty

MODELS

PCCS9RW Standard switch control



Front View

MARNING: This product may contain chemicals known to the State of California to cause cancer and birth defects or other reproductive harm. For more information, visit whelen.com/regulatory.

Code No. P12647D - 8/2023

